

Agasthya 2013 Series Helium Purity Analyzer Model BI 610



Features:

- ❖ 32-Bit Cortex-M3 ARM Processor
- ❖ Long life Thermal Conductivity He sensor
- ❖ RS 485, supports MODBUS protocol
- ❖ PTFE tubing and corrosion-resistant components for internal sample health
- ❖ Flow meter for flow regulation

Agasthya 2013 Series Helium Purity Analyzer Model BI 610

Technical Specification

Method of Detection	: Thermal Conductivity sensor for He
Range Available	: 0-100% scalable
Resolution	: 0.01%
Accuracy & Repeatability	: $\pm 1\%$ of FS
Drift	: 0.5% per year
Response Time (T-90)	: ≤ 10 seconds
Display	: Touch Screen LCD LED
Power	: 80 to 230 VAC 50 Hz
Power Consumption	: 8 Watts
Digital Output	: RS485 with MODBUS Protocol
Analog Output	: 4-20 mA (max load resistance upto 500 Ω)
Relay Output	: 2 nos. of potential free contacts
Humidity	: 5-95% RH
Ambient Temperature Range	: 4 to 50°C
Flow Meter	: 0.1-1 LPM
Enclosure	: Wall, Panel, Rack & Table Top
Sample Connection	: 1/4 inch S.S. Connection
Area Classification	: General Purpose

Ordering Code

Basic Model	Technology	Enclosure Type	Display
610	TC – Thermal Conductivity	W - Wall	T - Touchscreen
		P - Panel	LCD
		R - Rack	LED
		TT - Tabletop	

For Example:

Model No. 600-TC-P-LED

Helium Purity Analyzer Thermal Conductivity Sensor, Panel Mount & LED Display

BHOOMI[®] Process Management Pvt. Ltd.
(Formerly known as Bhoomi Analyzers)

Head Office :

409, 4th Floor, Avior (Nirmal Galaxy),
Next to Deep Mandir, Opp. Johnson & Johnson,
L.B.S. Marg, Mulund (W), Mumbai - 400080.

Manufacturing Unit :

201, 207, 208, G Wing, Udyog Bhavan No.s: 2,
Plot No.: K-3, Additional Ambarnath MIDC,
Ambarnath-East-421506, Dist.: Thane, Maharashtra.

Phone : + 91-22-25916858, 25916916 Cell : +91 7777071509

Email : sales@bhoomiltd.com, service@bhoomiltd.com

Website : www.bhoomiltd.com